

9-13-00

A

## PATENT

Attorney Docket No. YMEDIA.007A

Date: September 12, 2000

Page 1

ASSISTANT COMMISSIONER FOR PATENTS  
WASHINGTON, D.C. 20231  
ATTENTION: BOX PATENT APPLICATION

Sir:

Transmitted herewith for filing is the patent application of

Inventor: Sarit Neter

For: METHODS AND SYSTEMS OF DETECTING DEFECTIVE IMAGIN PIXELS AND PIXEL  
VALUES

Enclosed are:

- (X) Eight (8) sheets of drawings.
- (X) Recordation form cover sheet with 2-page assignment.
- (X) A verified statement to establish small entity status under 37 CFR 1.9 and 37 CFR 1.27.
- (X) A power of attorney form and copy of assignment.
- (X) Initial signed declaration by inventor.
- (X) Return prepaid postcard.

## CLAIMS AS FILED

| FOR  | NUMBER<br>FILED | NUMBER<br>EXTRA | RATE  | FEE   |
|--|-----------------|-----------------|-------|-------|
| Basic Fee  |                 |                 | \$345 | \$345 |
| Total Claims   | 34 - 20 =       | 14 ×            | \$9   | \$126 |
| Independent Claims   | 7 - 3 =         | 4 ×             | \$39  | \$156 |
| If application contains any multiple dependent claims(s), then add |                 |                 | \$130 | \$-0- |
| <b>TOTAL FILING<br/>FEE</b>  |                 | \$627           |       |       |

- (X) A check in the amount of \$627 to cover the filing fee is enclosed.
- (X) A check in the amount of \$40.00 to cover the assignment recording fee.
- (X) The Commissioner is hereby authorized to charge any additional fees which may be required, now or in the future, or credit any overpayment to Account No. 11-1410. A duplicate copy of this sheet is enclosed.
- (X) Please use Customer No. 20,995 for the correspondence address.

*David N. Weiss*  
David N. Weiss  
Registration No. 41,371  
Attorney of Record

L:\DOCS\DNW\DNW-2446.DOC: clk  
091100

09/12/00  
JC927 U.S. PTO

JC511 U.S. PTO  
09/659355  
09/12/00

09/12/00 09:43:00

Applicant or Patentee: Sarit Neter  
Application or Patent No.: Unknown  
Filed or Issued: Herewith

Attorney's Docket No.: YMEDIA.007A  
Page 1

For: **METHODS AND SYSTEMS OF DETECTING DEFECTIVE IMAGING PIXELS AND PIXEL VALUES**

---

**VERIFIED STATEMENT (DECLARATION) CLAIMING SMALL-ENTITY STATUS**

I, the undersigned, do hereby declare that:

☒ I am an official of the small business concern empowered to act on behalf of the concern identified below:

NAME OF CONCERN: YMedia Corporation

ADDRESS OF CONCERN: 23172 Plaza Pointe Drive, Suite 285, Laguna Hills, California 92653

I further declare that the above-identified small business concern qualifies as a small business concern as defined in 13 CFR 121.12, and reproduced in 37 CFR 1.9(d), for purposes of paying reduced fees to the United States Patent and Trademark Office, in that the number of employees of the concern, including those of its affiliates, does not exceed 500 persons. For purposes of this statement, (1) the number of employees of the business concern is the average over the previous fiscal year of the concern of the persons employed on a full-time, part-time or temporary basis during each of the pay periods of the fiscal year, and (2) concerns are affiliates of each other when either, directly or indirectly, one concern controls or has the power to control the other, or a third party or parties controls or has the power to control both. I further declare that rights under contract or law have been conveyed to and remain with the small business concern identified above with regard to the invention described in the patent or application identified above.

The individual, concern or organization identified above has not assigned, granted, conveyed or licensed, and is under no obligation under contract or law to assign, grant, convey or license, any rights in the invention to any person who would not qualify as an independent inventor under 37 CFR 1.9(c) if that person had made the invention, or to any concern which would not qualify as a small business concern under 37 CFR 1.9(d) or a nonprofit organization under 37 CFR 1.9(e).

If the rights held by the above-identified individual, concern or organization are not exclusive, each individual, concern or organization having rights in the invention are identified below. Each such individual, concern or organization must file separate verified statements averring to their status as small entities.

**\*NOTE: Separate verified statements are required from each named person, concern or organization having rights to the invention averring to their status as small entities. (37 CFR 1.27).**

FULL NAME:

ADDRESS:

☐ INDIVIDUAL      ☐ SMALL BUSINESS CONCERN      ☐ NONPROFIT ORGANIZATION

I acknowledge the duty to file, in this application or patent, notification of any change in status resulting in loss of entitlement to small-entity status prior to paying, or at the time of paying, the earliest of the issue fee or any maintenance fee due after the date on which status as a small entity is no longer appropriate. (37 CFR 1.28(b)).

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under section 1001 of Title 18 of the United States Code, and that such willful false statements may jeopardize the validity of the application, any patent issuing thereon, or any patent to which this verified statement is directed.

NAME OF PERSON SIGNING: Ian Olsen

Applicant or Patentee: Sarit Neter  
Application or Patent No.: Unknown  
Filed or Issued: Herewith

Attorney's Docket No.: YMEDIA.007A  
Page 2

## For: METHODS AND SYSTEMS OF DETECTING DEFECTIVE IMAGING PIXELS AND PIXEL VALUES

TITLE OF PERSON (if not an owner or individual): President & CEO

ADDRESS OF PERSON SIGNING: 23172 Plaza Pointe Drive, Suite 285, Laguna Hills, California 92653

SIGNATURE:

DATE:

L:\DOCS\DNW\DNW-2304.DOC: clk  
070700

[illegible]

**METHODS AND SYSTEMS OF DETECTING DEFECTIVE IMAGING PIXELS  
AND PIXEL VALUES**

5

Claim of Priority

This patent application claims the benefit of U.S. Provisional Application No. 60/149,796 filed August 19, 1999, and U.S. Application Nos. 09/495,971, 09/496,364, 09/496,533, 09/496,607, filed February 2, 2000, which are hereby incorporated herein by reference in their entirety.

10

Background of the Invention

Field of the Invention

The present invention relates to imaging devices and, more particularly, to methods and systems for compensating for defective pixels and pixel values.

Description of the Related Art

15

Conventional integrated circuit imaging devices include an array of light detecting elements or pixels which are interconnected to generate an analog signal representation of an image illuminating the device. Two common examples of conventional integrated circuit imaging devices are a charge coupled device (CCD) and a complementary metal oxide semiconductor (CMOS) image sensing device. Conventional imaging devices typically include one or more light detecting elements and charge storage elements. Such integrated circuits employ a light detecting element, such as a photodiode or phototransistor, that is capable of conducting current approximately proportional to the intensity of the light illuminating the element and a charge storage element. The collection of the signals from the pixels represents the image of the scene viewed by the array.

20

25

In order to produce a color image, the imaging devices separate the light into various color components by filtering the light before the light strikes the light detecting elements. The array of light detecting elements is often deposited with a filter layer such that neighboring pixels may have different color filters and organized in a particular pattern.

30

Because each pixel is typically only capable of detecting a single color, conventional imaging devices utilize a process by which all of the color components are reconstructed for each pixel in order to maintain the original unfiltered array resolution. To reconstruct the color components, conventional imaging devices use a process of color interpolation that is performed after an analog signal associated with each pixel has been digitized. The conventional process of color interpolation performed after an analog signal associated with each pixel has been digitized requires conversion from analog to digital (A/D) and may require extensive computations in order to achieve a high quality color presentation of the image. The A/D conversion and extensive computations may require hardware, such as analog-to-digital (A/D) converters, memory, processors and software. The hardware and software may add to the complexity, size and expense of the imaging device and reduce the speed of the imaging process.

Each pixel represents a sample of the scene and hence is a data value in the two-dimension image produced by the imaging system. Defective pixels, commonly referred to as 'bad pixels,' are caused by an array defect and do not provide the correct light intensity value. Bad pixels appear as image artifacts that can reduce the image quality significantly. In particular, a bad pixel produces an output signal that significantly deviates from the mean output level of adjacent pixels when the exposure level of all pixels is unified. Pixels that are significantly brighter than adjacent pixels in a unified dark frame are commonly referred to as a 'hot pixels,' while pixels that are significantly darker than adjacent pixel in a unified bright frame are commonly referred to as 'dead pixels.'

The defective pixels are typically distributed in a random manner. However, a 'bad column' (i.e., a complete column is defective) or a blemish (i.e., a cluster of neighboring pixels is defective) may occur and are typically discarded by the manufacturer. Sensor arrays that contain random defective pixels in an amount that does not exceed a given limit are released, and the remaining bad pixels are sometimes be corrected in some other manner.

Some CCD and CMOS integrated circuit color imaging devices employ a process of bad pixel detection and correction. Conventionally, the bad pixel detection

step is performed off-line by the manufacturer, before the imaging device is shipped. A bad pixel list is typically stored in an EEPROM lookup table. When the imaging device is later used in a product, such a camera, the lookup table is read to locate the bad pixels. Once the bad pixel locations are read, the values of the bad pixels are discarded when constructing an image based upon the imaging device readout. The bad pixel correction is performed by substituting the bad pixel value with the value of a pre-specified other pixel, wherein a lookup table created during the manufacturing process is used to identify the pre-specified other pixel whose value is to be used. This conventional correction step is typically performed after the analog signal for each pixel has been digitized.

The conventional bad pixel detection and correction process described has several significant drawbacks. For example, some of the array defects that cause bad pixels are temperature and gain dependent, and thus may appear and disappear during operation. Because these bad pixels are not consistently "bad," they may not be detected by the manufacturer, and hence, may not be corrected. In addition, because the detection step is performed off-line by the manufacturer, a non-volatile storage device is needed to store the defect pixel list. Adding a storage unit disadvantageously increases the cost and complexity of the system.

#### Summary of the Invention

The present invention relates to methods and systems for the detection of defective pixels within an array of sensor cells and for correction or compensating for the defective pixels. The effect these defective pixels have on image quality is thereby reduced. In particular, one embodiment of the integrated circuit imaging system of the present invention includes an on-line, on the fly defective pixel detection and correction process that provides high speed operation, reduced storage requirements, and improved detection of defective pixels as compared to conventional systems.

For example, one embodiment of the present invention provides an on-line bad pixel detection and correction process that compares a first pixel readout value with the readout values of other pixels in first pixel's local neighborhood. The average, weighted mean or median value of the readout values of the other pixels may be

calculated. The calculated value may also include the first pixel readout value. This calculated value may be used in the comparison with the first pixel readout value. When the first pixel readout value varies by more than a first amount as compared with the value calculated based on the readout values of the neighboring pixels, a value  
5 related to the readout values of the neighboring pixels is used in place of the first pixel readout value.

One significant advantage of the present invention is that the correction or compensation for some or all bad pixels may be performed, including bad pixels and bad pixel values that are introduced during the real-time operation of the imaging  
10 system due to temperature and/or gain changes. Thus, bad pixels and bad pixel values may be detected while the imaging device is used on-line by a consumer or other end-user, such as in a camera or the like. By contrast, conventional techniques only correct bad pixels that were identified during the manufacturing process, before the imaging device is delivered to the end-user.

Another significant advantage of the present system is that it prevents the loss of edges in a reconstructed image. Conventional processes may destroy edges via the correction process since often times the correction involves a low pass filter that reduces the high frequency content of the reconstructed image.  
15

Still another advantage of the present system is that, because the present invention corrects bad pixels on-line, the need for bad pixel look up tables is reduced or eliminated. Thus, the cost and complexity associated with non-volatile storage units conventional used to store bad pixel lookup tables, such as those used by conventional systems is reduced or eliminated. Also, the system is advantageously able to correct individual bad pixels distributed randomly in an array, rather than solely a cluster or  
20 column of bad pixels.

In one embodiment, the imaging system includes an array of pixel sensor cells arranged in rows and columns, a plurality of detection circuits, and an array controller with a programmable readout mode. The system may comprise a monochrome or a color imaging system. If the imaging system is a color imaging system, then a color  
25 filter layer comprised of several color filter components organized in a predefined pattern may be deposited on or otherwise placed over the pixel sensor array. For  
30

example, in one embodiment, the color filter comprises a primary color system with red, green, and blue filters (RGB) or a complementary color system arranged in a Bayer pattern.

In one embodiment, the imaging system may further include amplification stages, analog-to-digital conversion units, memory units and various other signal processing blocks either 'on-chip,' that is, on the same chip as the imaging device, such as on the same chip as a CMOS integrated circuit imaging device, or 'off-chip,' that is on a separate chip or circuit board than the imaging device.

The imaging system may be a monochrome imaging system employing a CMOS integrated circuit, or may be color imaging system employed, by way of example, a CCD imaging device with appropriate color filters. In one embodiment, a signal processing circuit is used to detect and correct defective or bad pixels. The signal processing circuit treats bad pixels as random shot noise and utilizes non-linear conditional filtering for detecting and eliminating or excluding the bad or noisy pixels.

In one embodiment, the color imaging system employs an on-the-fly bad pixel detection and correction process using a signal processing procedure performed during readout of the imaging device output signals, while those signals are still in analog form. This on-the-fly bad pixel detection and correction process is capable of random access readout and includes programmable gain amplifiers, an A/D converter, one or more registers for temporary storage, and a signal processing block. In this on-the-fly mode of operation, the signal processing unit performs the detection step via horizontal, vertical and diagonal conditional median filters. If the pixel whose value is being examined, which may be the middle or center pixel within a horizontal, vertical or diagonal set of pixels, the is not within the condition limits, its value is replaced in the correction step. The replacement value may be determined by the directional median that possesses the minimum variation. The value chosen can be, by way of example, a median, weighted mean, or average value of two or more pixels in the neighborhood in which the bad pixel is situated.

In one embodiment, the imaging system uses random access readout. However the imaging system may also use a pipeline architecture, a parallel readout architecture, or other architectures. A pipeline architecture may use a sequential readout via row and



column shift registers and several line storage units, such as random access memory (RAM) in digital domain or capacitors in analog domain. In a parallel readout architecture, several pixels per column can be read simultaneously via independent column buses and stored in registers.

5           In still other embodiments, the imaging system further combines the on-the-fly bad pixel detection & correction with various readout modes such as windowing and sub-sampling. In one embodiment, the imaging system uses additional signal processing such as on-the-fly color interpolation.

10           The pixels of the imaging system are not required to be organized in a rectangular matrix. A similar implementation can provide on-the-fly bad pixel correction and detection for color imaging system and/or different pixel topography via modification to the readout control, the pixel neighborhood size and configuration. For example, a color imaging system with an RGB Bayer pattern may use a 5 x 5 pixel neighborhood out of which pixels of the same color component as the pixel whose value  
15           is being examined are selected for the filtering process.

#### Brief Description of the Drawings

Figure 1 illustrates one embodiment of an imaging system coupled to a television.

20           Figure 2 illustrates one embodiment of an imaging system coupled to a computer.

Figure 3 illustrates a Bayer pattern color filter for the primary color system.

Figure 4 illustrates one embodiment of a CMOS integrated circuit, monochrome imaging system that supports on-the-fly bad pixel detection & correction.

25           Figures 5A-B illustrate one embodiment of an on-the-fly bad pixel detection and correction process implemented by the circuit of Figure 4.

Figure 6 illustrates an exemplifying 3 x 3 block of pixels within the system of Figure 4.

30           Figure 7 illustrates an exemplifying 5 x 5 block of pixels using the primary color scheme and the Bayer color pattern where the middle pixel is red.

Figure 8 illustrates an exemplifying 5 x 5 block of pixels using the primary color scheme and the Bayer color pattern, where the middle pixel is blue.

Figure 9 illustrates an exemplifying circuit used to locate a minimum pixel value, an intermediate pixel value, and a maximum pixel value in a group of three pixels.

#### Detailed Description of Preferred Embodiments

The present invention relates to a novel imaging system that provides flexible addressing and processing of imaging pixel sensor elements. The novel architecture of the present invention allows for a highly integrated, low cost imager with high speed performance and good image quality. Defective or bad pixels within an array of active or passive pixel sensor cells are detected and compensated for, thereby reducing or eliminating the visible effects the bad pixels may have on resulting images. In one embodiment, the imaging system provides an on-line, on-the-fly bad pixel detection and correction process that provides high speed operation, reduced non-volatile storage requirements, and good performance.

For example, one embodiment of the present invention provides an on-line bad pixel detection and correction process and circuit that compares a first pixel readout value with another value derived at least in part on the readout values of other pixels in first pixel's local neighborhood. Based on this comparison, a determination is made as to whether the first pixel readout value is valid. If it is determined that the first pixel readout is not valid, a value related to the readout values of the neighboring pixels is used in place of the first pixel readout value, and is sent downstream as part of the image data to be stored, processed, displayed and/or printed. Otherwise, the first pixel readout value may be used. The term pixel value, as used herein, may be an analog or digital readout value, a digitized version of the analog readout value, or other transformed pixel readout value.

The exemplifying imaging systems described below use a monochrome CMOS integrated circuit, an array of pixels organized in a rectangular matrix, and, in a color version, a color filter with a primary color system (RGB) in a Bayer color pattern. However, other embodiments use a charge coupled device (CCD) or may use other imaging technologies. Likewise, the imaging systems of the present invention may be

implemented with another color system, such as the complimentary color system (Yellow, Cyan and Magenta) and/or another color pattern. In addition, the imaging system of the present invention may be implemented with the pixels organized in another pixel matrix or pixel topography. For example, the array does not have to be rectangular or have a regular pattern of pixels.

The imaging system may also include either on-chip or off-chip amplification stages, analog-to-digital conversion units, memory units and various other signal processing blocks. In addition, the system may further comprise a micro-lenses layer. For example, in one embodiment, the bad pixel detection and correction system resides with a CMOS sensor array on the same chip or substrate, such as in a CMOS integrated circuit color imaging device. In another embodiment, the bad pixel detection and correction system resides in a separate companion chip and is used in conjunction with a CCD sensor array located on a separate substrate.

Figures 1 and 2 illustrate exemplifying systems incorporating embodiments of the novel imaging system 100, 122. Figure 1 illustrates one embodiment of an imaging system 100 coupled to a television 116 via a coax cable 114. The exemplifying system 100 includes a lens 102, a sensor array 104 which may include one or more color filters, a readout control 106, gain amplifiers 108 for each color, an NTSC encoder 110 including gamma correction and a power supply 112 used to power the camera circuitry and sensor array 104. The lens 102 may be used to focus images onto the sensor array 104, and/or may be used as a protective covering for the sensor array 104. In one embodiment, the imaging system 100 is a video camera. In other embodiments, the imaging system 100 may be implemented in security cameras, digital cameras, camcorders, video telephones and the like.

Figure 2 illustrates one embodiment of an imaging system 122 coupled to a computer 126 via a universal serial bus (USB) cable 124. The exemplifying system 122 includes a lens 102, a sensor array 104 which may include one or more color filters, a readout control 106, gain amplifiers 108 for each color, an analog to digital converter 118, a USB interface 120 and a power supply 112 used to power the imaging system circuitry and sensor array 104. In one embodiment, the imaging system 122 is a video

camera. In other embodiments, the imaging system 122 may be similarly implemented in security cameras, digital cameras, camcorders, video telephones and the like.

Figure 3 illustrates a conventional Red, Green and Blue (primary color system) Bayer color pattern 130 for a color filter that is deposited on an array of pixel cells that detect light. The pattern core is a group of 2 by 2 pixels that contains 2 green components 134, 136, one red component 132 and one blue component 138. The 2 green components 134, 136 are diagonal neighbors, and the red and the blue components 132, 138 are diagonal neighbors. Thus, the green resolution of the array is reduced by a ratio of 2:1 horizontally only, while the red and the blue resolution is reduced by a ratio of 2:1 horizontally and vertically. The pattern 130 exploits the fact that the human eye perceives intensity edges better than color edges and that the green component contains the highest amount of intensity information.

Figure 4 illustrates one embodiment of a circuit which utilizes the novel bad pixel detection and correction technique of the present invention. The illustrated embodiment is a CMOS integrated circuit, monochrome imaging system 198 that supports on-the-fly bad pixel detection & correction via programmable pixel readout circuitry 212, 214 and signal processing circuitry 200, 208. Other embodiments may employ CCD integrated circuit and/or different color filters. The signal processing unit may be analog or digital. The signal processing unit may be implemented using dedicated hardwired circuitry, a general purpose processor that may also perform other tasks, or a programmable circuit, such as a DSP, optimized for signal processing functions.

As illustrated in Figure 4, the system 198 includes a bad pixel detection and correction unit 200, a pixel data output line 201, an analog-to-digital (A/D) converter 208, an analog amplifier 210, a column address decoder 212, a row address decoder 214, a pixel address generator 216, a row coordinate line 226, a column coordinate line 230, a frame synchronization signal 218, a line synchronization signal 220, a pixel clock signal 222, a control signal 224, a first column readout line 234, a second column readout line 236, a third column readout line 238, a first switch 240, a first column buffer 246, a second switch 242, a second column buffer 248, a third column readout line 238, a third switch 244, a third column buffer 250, a first row readout line 262, a

second row readout line 264, a third row readout line 266, a first row buffer 252, a second row buffer 254, a third row buffer 256, a first pixel 258, a second pixel 260, a third pixel 266, a fourth pixel 268, and an optional storage unit 232. In one embodiment, the amplifier 210 is a programmable gain amplifier.

Figure 4 presents an implementation for monochrome on-the-fly bad pixel detection & correction when windowing and sub-sampling is not active. The present invention, however, is not limited to a monochrome imager. Nor is the present invention limited in its mode of operation and can be realized to support window and sub-sampling via the programmable readout control circuitry 212, 214. In the description herein, a "programmable" component refers to a component that responds to a command from an end-user of the imaging system or to a command issued by internal firmware according to firmware stored in the imaging system. For example, if an end-user chooses a 'zoom' function or a 'preview' function on a video camera containing the imaging system of the present invention, the imaging system directs the programmable components to act in a predefined manner according to firmware stored in the imaging system.

In Figure 4, the system 198 contains a signal processing unit 200 that allows bad pixel detection and correction, as described below with reference to Figures 5A-B. The signal processing unit 200 treats the bad pixels as random 'shot noise' and utilizes non-linear conditional filtering for detecting and eliminating or excluding the noisy or defective pixels.

The imaging system of the present invention, such as the monochrome system 198 in Figure 4, employs an on-the-fly bad pixel detection and correction process that is a signal processing procedure performed during the sensor readout stage. The system 198 of Figure 4 may perform a random access readout of the pixels using the column and row decoders 212, 214. In on-the-fly bad pixel detection and correction, the signal processing unit 200 illustrated in Figure 4 performs bad pixel detection step via horizontal, vertical and diagonal conditional median filters within the signal processing unit 200. If a middle or center pixel is not within the condition limits, it is replaced in the correction step by a value determined by the directional median that possesses the

minimum variation, as described below. The value chosen can be either the median or an average.

Figures 5A-B illustrate one embodiment of an on-the-fly bad pixel detection and correction process in full resolution mode implemented by the circuit of Figure 4. The present invention advantageously permits bad or defective pixels to be detected even after the imaging device has been provided to an end-user, such as a consumer, in a camera or the like. Thus, for example, the present invention allows bad pixel detection to be performed on-the-fly, in response to an end-user capturing an image using the camera, or during a calibration procedure automatically initiated when the user turns on the camera.

Figure 6 illustrates an exemplifying 3 x 3 block of pixels within the system of Figure 4. In Figure 6, the block 300 comprises a first pixel 302, a second pixel 304, a third pixel 306, a fourth pixel 308, a fifth pixel 310, a sixth pixel 312, seventh pixel 314, an eighth pixel 316, and a ninth pixel 318. Figure 6 also shows a portion of a next column in the array of Figure 4. The next column comprises a tenth, eleventh and twelfth pixels 320, 322, 324. Figure 6 also shows a portion of the next row in the array of Figure 4. The next row comprises a thirteen, fourteenth and fifteenth pixels 326, 328, 330.

The process illustrated in Figures 5A-B is described with reference to Figures 4 and 6. In a start state 502 of Figure 5A, the column and row readout circuits 212, 214 illustrated in Figure 4A read out a 3 x 3 pixel block or neighborhood 300, such as that illustrated in Figure 6, of pixel sensor element values. The pixel values may be those for an image taken by an end-user using an imaging system, such as those illustrated in Figures 1 and 2. In a process state 504, the pixel address generator 216 illustrated in Figure 4 prepares four 1 x 3 sub-blocks comprised of pixels in a line: a middle horizontal sub-block, a middle vertical sub-block, and a first and second middle diagonal sub-blocks. The 1 x 3 sub-blocks may also be referred to as groups, local neighborhoods or subsets. The 1 x 3 middle horizontal sub-block comprises the fourth, fifth and sixth pixels 308, 310, 312. The middle vertical sub-block comprises the second, fifth and eighth pixels 304, 310, 316. The first middle diagonal sub-block

comprises the first, fifth and ninth pixels 302, 310, 318. The second middle diagonal pixel sub-block comprises the third, fifth and seventh pixels 306, 310, 314.

In a process state 506, the bad pixel detection and correction unit 200 calculates the distribution for each 1 x 3 sub-block, i.e., the absolute difference between the highest and the lowest pixel sensor element values in a 1 x 3 sub-block. In a process state 508, the bad pixel detection and correction unit 200 finds the 1 x 3 sub-block with the minimum variance, i.e., the block with smallest absolute difference. In a process state 510, the bad pixel detection and correction unit 200 determines the median value for each 1 x 3 sub-block by sorting the three pixel values in each 1 x 3 sub-block from lowest to highest. For example, if a 1 x 3 block has values of 10, 15 and 100, the median value would be 15.

In a decision block 512, the bad pixel detection and correction unit 200 determines whether the value of the original middle pixel 310 illustrated in Figure 6 exceeds the median values of the four 1 x 3 sub-blocks. If the original middle pixel 310 value exceeds the median values of the four 1 x 3 sub-blocks, then in a process state 514, the bad pixel detection and correction unit 200 replaces the original middle pixel 310 value with the median value of the 1 x 3 sub-block with the minimum or smallest variance found in process state 508. Effectively, the bad pixel detection and correction unit 200 picks the smoothest edge. The bad pixel detection and correction unit 200 then passes the replaced middle pixel value via pixel data output line 201 for further processing, as is performed on the other pixels. In a process state 516, the pixel address generator 216 and the bad pixel detection and correction unit 200, illustrated in Figure 4, advance to the next column, such that the middle pixel is now the sixth pixel 312 illustrated in Figure 6.

If the unit 200 determines that the original middle pixel 310 value does not exceed the median values of the four 1 x 3 sub-blocks, then in process state 516, the pixel address generator 216 and bad pixel detection and correction unit 200 advance to the next column, such that the middle pixel is now the sixth pixel 312 in Figure 6. In a decision block 366, the pixel address generator 216 determines whether it has exceeded the last column in the pixel array of Figure 4. If the pixel address generator 216 has not

exceeded the last column in the pixel array, the generator 216 and the bad pixel detection and correction unit 200 begin to process the next 3 x 3 block.

If the pixel address generator 216 has exceeded the last column in the pixel array of Figure 4, then in a process state 520, the generator 216 advances to the next row of pixel sensor elements, such that the middle pixel is now the eighth pixel 316. In a decision state 522, the address generator 216 determines whether it has exceeded the last row in the array of Figure 4. If the address generator 216 has not exceeded the last row in the array, the generator 216 and the bad pixel detection and correction unit 200 begin to process the next 3 x 3 block. If the address generator 216 has exceeded the last row in the array, the generator stops in a stop block 524.

The bad pixel detection and correction process may also be described via the following exemplary mathematical algorithm which may be implemented in software or hardware.

In this example, the pixel neighborhood used is a 3 x 3 group as follows:

$$\begin{matrix} X_{(0,0)}, X_{(0,1)}, X_{(0,2)} \\ X_{(1,0)}, X_{(1,1)}, X_{(1,2)} \\ X_{(2,0)}, X_{(2,1)}, X_{(2,2)} \end{matrix}$$

Then, using the digitized pixel values, the median values for the four 3-pixel subsets that include the middle pixel  $X_{(1,1)}$  are calculated, and the maximum and minimum median values are assigned correspondingly to the variables Max and Min as follows:

$$(1) \text{ Max} = \text{Maximum} [ \text{Median} (X_{(1,0)}, X_{(1,1)}, X_{(1,2)}), \text{Median} (X_{(0,1)}, X_{(1,1)}, X_{(2,1)}), \\ \text{Median} (X_{(0,0)}, X_{(1,1)}, X_{(2,2)}), \text{Median} (X_{(0,2)}, X_{(1,1)}, X_{(2,0)}) ]$$

$$(2) \text{ Min} = \text{Minimum} [ \text{Median} (X_{(1,0)}, X_{(1,1)}, X_{(1,2)}), \text{Median} (X_{(0,1)}, X_{(1,1)}, X_{(2,1)}), \\ \text{Median} (X_{(0,0)}, X_{(1,1)}, X_{(2,2)}), \text{Median} (X_{(0,2)}, X_{(1,1)}, X_{(2,0)}) ]$$

(3) The ratios of the middle pixel value to the Max value and to the Min value are compared to a threshold value. The threshold value is a predetermined value so chosen that if the above ratios are greater than the threshold, there is a statistically high likelihood that the middle pixel value is in error.

$$\text{Limit} = \left( \frac{X_{(1,1)}}{\text{Max}} \geq \text{Threshold} \right) \text{ or } \left( \frac{\text{Min}}{X_{(1,1)}} \geq \text{Threshold} \right)$$



(4) If ( *Limit* > 0 ) then the value of the middle pixel will be replaced with the median value of one of the four 3-pixel subsets. The median value of the subset with the smallest variance between the values of the most physically distant pixels within the subset will be used to replace the middle pixel value, as follows:

$$(5) \text{ Variance} = \text{Minimum} ( |X_{(1,0)} - X_{(1,2)}|, |X_{(0,1)} - X_{(2,1)}|, |X_{(0,0)} - X_{(2,2)}|, |X_{(0,2)} - X_{(2,0)}| )$$

(6) If *Variance*  $\in \{X_{(1,0)}, X_{(1,1)}, X_{(1,2)}\}$  Then

$$(7) X_{(1,1)} = \text{Median} (X_{(1,0)}, X_{(1,1)}, X_{(1,2)})$$

(8) If *Variance*  $\in \{X_{(0,1)}, X_{(1,1)}, X_{(2,1)}\}$  Then

$$(9) X_{(1,1)} = \text{Median} (X_{(0,1)}, X_{(1,1)}, X_{(2,1)})$$

(10) If *Variance*  $\in \{X_{(0,0)}, X_{(1,1)}, X_{(2,2)}\}$  Then

$$(11) X_{(1,1)} = \text{Median} (X_{(0,0)}, X_{(1,1)}, X_{(2,2)})$$

(12) If *Variance*  $\in \{X_{(0,2)}, X_{(1,1)}, X_{(2,0)}\}$  Then

$$(13) X_{(1,1)} = \text{Median} (X_{(0,2)}, X_{(1,1)}, X_{(2,0)})$$

Figure 9 illustrates an exemplifying circuit used to locate a minimum pixel value, an intermediate pixel value, and a maximum pixel value in a group of three pixels, such as one of the groups used in the above equations. This circuit may be implemented in a gate array, a field programmable gate array, a custom integrated circuit, using discrete logic, or in software. Optionally, the illustrated circuit may be repeated four times so that the pixels having the minimum, maximum, and intermediate value for each of the pixel groups  $(X_{(1,0)}, X_{(1,1)}, X_{(1,2)})$ ,  $(X_{(0,1)}, X_{(1,1)}, X_{(2,1)})$ ,  $(X_{(0,0)}, X_{(1,1)}, X_{(2,2)})$ ,  $(X_{(0,2)}, X_{(1,1)}, X_{(2,0)})$  may be located in parallel, thereby speeding the process. In another embodiment, to reduce circuitry, the location process may be serially performed using only one circuit.

In the illustrated example, pixel 1 corresponds to  $X_{(1,0)}$ , pixel 5 corresponds to  $X_{(1,1)}$ , and pixel 9 corresponds to  $X_{(1,2)}$ . The corresponding signs sgnA, sgnB, sgnC, of

the values of (pixel 1 - pixel 5), (pixel 5 - pixel 9), and (pixel 1 - pixel 9) are calculated. The signs of the results are used to address a look-up table. A positive sign is a "0" and a negative sign is a "1" for purposes of addressing. The lookup table maps the sign values into an identification of the pixel having the minimum value, the pixel having the maximum value, and the pixel having the minimum value. Thus, for example, if pixel 1 has a normalized value of 0.9, pixel 5 has a normalized value of 0.7, and pixel 9 has a normalized value of 0.8, then

sgnA is positive, or a "0"  
sgnB is negative, or a "1"  
sgnC is positive, or a "0"

Thus, the address is a 010. The location information at the location addressed by 010 identifies pixel 5 as having the minimum value, pixel value having a middle or intermediate value, and pixel 1 as having a maximum value. This location information may be then be used in calculating the distribution for each 1 x 3 sub-block, such as the difference between the highest and the lowest pixel element sensor value calculated at process state 506 in Figure 5. A similar circuit may be used to locate the highest, intermediate, and lowest median value from a group of median values, as performed in Equations 1 and 2 above.

It is important to note that the present invention is not limited to the embodiments discussed above. Other configurations may be implemented in accordance with the present invention. For example, in one embodiment, instead of or in addition to using straight 1 x 3 diagonal pixel sub-blocks, the address generator 216 and bad pixel detection and correction unit 200 may use a semi-diagonal 1 x 3 sub-block, such as the third, fifth and eighth pixels 306, 310, 316 of the block illustrated in Figure 6. In another embodiment, the address generator 216 may use a semi-diagonal 1 x 3 sub-block, such as the third, fifth and ninth pixels 306, 310, 318.

In still another embodiment, instead of or in addition to using the various 1 x 3 pixel sub-blocks discussed above, the address generator 216 and the bad pixel detection and correction unit 200 may use the complete 3 x 3 pixel neighborhood for one median filtering of the 9 elements. In still another exemplary embodiment, the mean values for all the blocks in the neighborhood are utilized, rather than median values.

In other embodiments, the bad pixel correction does not rely on minimum variance. For example, any of the median values can be chosen arbitrarily as the bad pixel replacement. Further, other values, such as the average values of some or all of the pixels in a block or group may be used.

5 In another embodiment, the address generator 216 and bad pixel detection and correction unit 200 may be configured to use other sizes of blocks or groups of pixels. For example, a 5 x 5 pixel block instead of a 3 x 3 block may be used, such that each median is selected from a 1 x 5 pixel sub-block instead of a 1 x 3 sub-block. In one embodiment, the pixel to be examined may be included in each 1 x 5 pixel sub-block.  
10 Rather than examining or testing the value of a center pixel within the 1 x 5 pixel sub-block, other pixels, such as other interior pixels having a pixels from the block positioned on two sides, may be used. Other embodiments may detect and correct pixel values using the values of pixels in a two dimensional neighborhood having other geometric shapes, such as circular or triangularly shaped neighborhoods, or using  
15 neighborhoods having irregular shapes. In still another embodiment, rather than using only pixels within a neighborhood in detecting and correcting pixel failures or misreadings for pixels within the neighborhood, all array pixels may be used, with more weight being given to those pixels proximate to a pixel whose value is being inspected and/or corrected.

20 Furthermore, for color imaging systems, a block with color filter components may be used. For example, a color imaging system with an RGB Bayer pattern may use a 5 x 5 pixel neighborhood out of which only pixels of the same color component as the middle pixel are used for the filtering process. Figure 7 illustrates an exemplifying 5 x 5 sub-block of pixels using the primary color scheme and the Bayer color pattern where  
25 the middle pixel 360 is red. In Figure 7, the pixel address generator 216 and the bad pixel detection and correction unit 200 applies the same general process shown in Figures 5A-B, except that only the red pixel values 352-368 are used in the 1 x 5 pixel sub-blocks.

30 Figure 8 illustrates an exemplifying 5 x 5 block of pixels using the primary color scheme and the Bayer color pattern, where the middle pixel 390 is blue. In Figure 8, the pixel address generator 216 and the bad pixel detection and correction unit 200 applies

the same general process shown in Figure 5A-B, except that only the blue pixel values 382-398 are used in the 1 x 5 pixel sub-blocks.

In one embodiment, the imaging system of the present invention uses random access readout. In other embodiments, the imaging system uses different implementations such as a pipeline architecture or a parallel readout architecture. A pipeline architecture may use a sequential readout via row and column shift registers and several line storage units, such as random access memory (RAM) in digital domain or capacitors in analog domain. This implementation may reduce the complexity of control circuitry, but may require additional memory or storage elements as compared to the embodiment illustrated in Figure 4. For example, referring to Figure 4, a RAM or 3 pixel register delay circuit may be inserted before the bad pixel detection and correction unit 200. The column address decoder may optionally be replaced with a simpler column shift register clocked by the line sync signal. Similarly, the row address decoder may optionally be replaced with a row shift register clocked by a frame sync signal. In a parallel readout architecture, several pixels per column can be read simultaneously via independent column buses and stored in registers.

In other embodiments, the imaging system further combines the on-the-fly bad pixel detection & correction with various readout modes such as windowing and sub-sampling. In one embodiment, the imaging system uses additional signal processing such as on-the-fly color interpolation.

As previously discusses, the pixels of the imaging system are not required to be organized in a rectangular matrix. A similar implementation can provide on-the-fly bad pixel correction and detection for a color imaging system and/or a different pixel topography via modification to the readout control, the pixel neighborhood size and configuration.

Thus, as described above, the various embodiments of the present invention advantageously provides an on-line, on the fly defective pixel detection and correction process that provides high speed operation, reduced storage requirements, and improved detection of defective pixels as compared to conventional systems.

The invention may be embodied in other specific forms without departing from its spirit or essential characteristics. The described embodiment is to be considered in

all respects only as illustrative and not restrictive and the scope of the invention is, therefore, indicated by the appended claims rather than the foregoing description. All changes which come within the meaning and range of equivalency of the claims are to be embraced within their scope.

WHAT IS CLAIMED IS:

1. An imaging system configured to compensate for one or more individual defective pixels in an array of pixel elements, the system comprising:

an array of pixel sensor elements;

5 a readout controller coupled to the array, the readout controller configured to read a block of pixels within the array, the block including a center pixel, the controller further configured to generate pixel addresses of at least three subsets of pixels within the block; and

10 a bad pixel detection and correction unit configured to determine a subset with a minimum variance, calculate a median of each subset, determine whether a value of the center pixel exceeds the medians of the subsets, and to replace the value of the center pixel with the median of the subset with the minimum variance if the value of the center pixel exceeds the medians of the subsets.

15 2. The imaging system as defined in Claim 1, wherein the array comprises a monochrome array.

3. The imaging system as defined in Claim 1, wherein the system further comprises a color filter deposited on the array.

4. The imaging system as defined in Claim 1, wherein the subsets comprise a horizontal row and two diagonal patterns.

20 5. The imaging system as defined in Claim 1, wherein the subsets comprise a vertical row and two diagonal patterns.

6. A method of correcting one or more individual defective pixels in an array of pixel elements, the method comprising:

25 reading a pixel block of an array of pixel sensor elements, the pixel block including an interior pixel;

30 selecting at least a first subset, a second subset and a third subset of pixels within the pixel block, the first subset comprising pixels arranged in a first diagonal pattern within the block, the second subset arranged in a second diagonal pattern within the block, the third subset arranged in a non-diagonal pattern;

calculating a variance between a highest and a lowest pixel sensor value within each subset;

identifying a subset with the least variance;

5 calculating a first value based on at least one of a median, average, and mean pixel sensor value for the corresponding three subsets;

determining whether a value for the interior pixel varies from the first value by more than a first amount; and

10 replacing the value for the interior pixel with a replacement value based on the pixel sensor values of the subset with the lowest variance if the value for the interior pixel varies from the first value by more than a first amount.

7. The method of Claim 6, further comprising:

selecting a fourth subset arranged in another non-diagonal pattern; and

calculating a variance between a highest and a lowest pixel sensor value within the fourth subset.

15 8. The method of Claim 6, wherein the non-diagonal pattern is horizontal.

9. The method of Claim 6, wherein the non-diagonal pattern is vertical.

10. The method of Claim 6, wherein the act of reading a pixel block comprises reading a 3 x 3 pixel block.

20 11. The method of Claim 6, wherein the act of reading a pixel block comprises reading a 5 x 5 pixel block.

12. A method of detecting a defective pixel element within an array of pixel elements in an imaging device while the imaging device is in use by an end-user, the method comprising:

capturing an image taken by the end-user using the imaging device;

25 for the captured image, comparing a first pixel element value with a second value related to at least element values of other imaging pixel elements in a first group;

determining from the comparison if the first pixel element value is in error; and

substituting a third value related to the value of at least one of the other pixels elements at least partly in response to determining the first pixel element value is error.

13. The method as defined in Claim 12, wherein the comparison act includes  
5 comparing the value of the first pixel element with the median value of the first group of pixels.

14. The method as defined in Claim 12, wherein the first group include at least two pixel elements adjacent to the first pixel element.

15. The method as defined in Claim 12, wherein the second value is also  
10 related to the first pixel element value.

16. The method as defined in Claim 12, wherein the third value is related to the median value of at least two other pixel values.

17. The method as defined in Claim 12, wherein the imaging device is a color imaging device, and the other pixels whose values are compared to the first pixel  
15 value are intended to sense the same color as the first pixel element.

18. The method as defined in Claim 12, wherein the imaging device is a monochrome imaging device.

19. An imaging system configured to compensate for one or more individual defective pixels in an imaging array, the system comprising:  
20

a readout controller coupled to the imaging array, the readout controller configured to read a group of pixels within the array;

a defective pixel detection circuit configured to determine when at least a first pixel value associated with a first pixel within the group of pixels varies from a second value related to at least one other pixel within the group of pixels  
25 by a first amount; and

a pixel compensation circuit configured to replace the value of the first pixel with a third value related to at least one other pixel within the group of pixels when the first pixel value varies by more than the first amount from the second value.

20. The imaging system as defined in Claim 19, wherein the second value is a median value of a plurality pixel values of pixels within the group of pixels.



21. The imaging system as defined in Claim 19, wherein the second value is an average value of a plurality pixel values of pixels within the group of pixels.

22. The imaging system as defined in Claim 19, wherein the third value is related to the median value of a plurality pixel values of pixels within the group of pixels.

23. The imaging system as defined in Claim 19, further comprising a color filter overlaying at least a portion of the array.

24. The imaging system as defined in Claim 19, wherein the array is a CMOS array.

25. The imaging system as defined in Claim 19, wherein the array is a CCD array.

26. A camera system, comprising:

an imager, including a plurality of pixels;

a lens overlaying at least a portion of the imager;

a readout circuit coupled to the imager, the readout circuit configured to read imager pixel values;

a defective pixel detection circuit configured to determine if a first pixel is defective by examining the pixel values of a plurality of pixels readout by the readout circuit;

a pixel compensation circuit configured to substitute the value of the first pixel with a value related to at least one other pixel value readout by the readout circuit; and

a power supply used to power the readout controller, the defective pixel detection circuit, and the pixel compensation circuit.

27. The camera system as defined in Claim 26, wherein the camera system is a video camera.

28. The camera system as defined in Claim 26, further comprising an NTSC encoder coupled to the readout circuit.

29. The camera system as defined in Claim 26, wherein the camera system is located on a phone.

30. The camera system as defined in Claim 26, further comprising a color filter positioned over at least a portion of the imager.

31. A method of detecting a defective pixel element within pixel elements in an imaging device using an image captured by the end-user, the method comprising:

5 for the captured image, comparing a first pixel element value with a second value related to at least element values of pixel elements in a two dimensional neighborhood;

determining from the comparison if the first pixel element value is in error; and

10 substituting the first pixel element value with a third value related to a value of at least one of the other pixels elements in the two dimensional neighborhood.

32. The method as defined in Claim 31, wherein the second value is related to at least two element values corresponding to at least two pixels on opposite sides of the first pixel element.

33. The method as defined in Claim 31, wherein the comparison includes determining if the first pixel element value varies from the second value by more than a threshold amount.

34. An imaging system comprising:  
20 an imager including a plurality of pixel sensor elements;  
a controller coupled to the imager, the controller configured to read pixel sensor element values;

25 a defective pixel detection circuit configured to determine when at least a first pixel value associated with a first pixel sensor element within a two dimensional neighborhood is in error by comparing the at least first pixel value to a second value related to at least one other pixel element within the two dimensional neighborhood; and

30 a pixel compensation circuit configured to replace the value of the first pixel element with a third value related to at least one other pixel element within the two dimensional neighborhood.

# METHODS AND SYSTEMS OF DETECTING DEFECTIVE IMAGING PIXELS AND PIXEL VALUES

## Abstract of the Disclosure

5           The present invention is related to methods and systems for detecting defective  
imaging array pixels and providing correction, thereby reducing or eliminating visible  
image artifacts. One embodiment of the present invention provides an on-line bad pixel  
detection and correction process that compares a first pixel readout value with a first  
value related to the readout values of other pixels in first pixel's local neighborhood.  
10       When the first pixel readout value varies by more than a first amount as compared with  
the first value, a second value related to the readout values of the neighboring pixels is  
used in place of the first pixel readout value.

15

L:\DOCS\DNW\DNW-2122.DOC  
041200




FIG. 1




FIG. 2




FIG. 3





FIG. 4



FIG. 5

FIG. 5A

SCAN 12








FIG. 5B

FIG. 6




FIG. 7





FIG. 8





**DECLARATION - USA PATENT APPLICATION**

As a below named inventor, I hereby declare that:

My residence, post office address and citizenship are as stated below next to my name;

I believe I am an original, first and joint inventor of the subject matter which is claimed and for which a patent is sought on the invention entitled METHODS AND SYSTEMS OF DETECTING DEFECTIVE IMAGING PIXELS AND PIXEL VALUES; the specification of which is attached hereto;

I hereby state that I have reviewed and understand the contents of the above identified specification, including the claims, as amended by any amendment referred to above;

I acknowledge the duty to disclose information which is material to patentability as defined in Title 37, Code of Federal Regulations, § 1.56;

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code and that such willful, false statements may jeopardize the validity of the application or any patent issued thereon.

-----  
Full name of sole inventor: **Sarit Neter**

Inventor's signature *Sarit Neter*

Date August 24, 2005

Residence: 15 Highland View, Irvine, California 92612

Citizenship: Israeli

Post Office Address: **Same as above.**

Send Correspondence To:  
KNOBBE, MARTENS, OLSON & BEAR, LLP  
**Customer No. 20,995**

## IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

|           |   |                             |   |
|-----------|---|-----------------------------|---|
| Applicant | : | Sarit Neter                 | ) |
|           |   |                             | ) |
| App. No.  | : | Unknown                     | ) |
|           |   |                             | ) |
| Filed     | : | Herewith                    | ) |
|           |   |                             | ) |
| For       | : | METHODS AND SYSTEMS OF      | ) |
|           |   | DETECTING DEFECTIVE IMAGING | ) |
|           |   | PIXELS AND PIXEL VALUES     | ) |
|           |   |                             | ) |
| Examiner  | : | Unknown                     | ) |

ESTABLISHMENT OF RIGHT OF ASSIGNEE TO TAKE ACTION  
AND  
REVOCATION AND POWER OF ATTORNEY

Assistant Commissioner for Patents  
 Washington, D.C. 20231

Dear Sir:

The undersigned is empowered to act on behalf of the assignee below (the "Assignee"). A true copy of the original Assignment of the above-captioned application from the inventor(s) to the Assignee is attached hereto. This Assignment represents the entire chain of title of this invention from the Inventor(s) to the Assignee.

I declare that all statements made herein are true, and that all statements made upon information and belief are believed to be true, and further, that these statements were made with the knowledge that willful, false statements and the like so made are punishable by fine or imprisonment, or both, under 18 U.S.C. § 1001, and that willful, false statements may jeopardize the validity of the application, or any patent issuing thereon.

The undersigned hereby revokes any previous powers of attorney in the subject application, and hereby appoints the registrants of Knobbe, Martens, Olson & Bear, LLP, 620 Newport Center Drive, Sixteenth Floor, Newport Beach, California 92660, Telephone (949) 760-9502, **Customer No. 20,995**, as its attorneys with full power of substitution and


App. No. : Unknown  
Filed : Herewith

revocation to prosecute this application and to transact all business in the U.S. Patent and Trademark Office connected herewith. This appointment is to be to the exclusion of the inventor(s) and his attorney(s) in accordance with the provisions of 37 C.F.R. § 3.71.

Please use **Customer No. 20,995** for all communications.

YMedia Corporation

Dated: 8-28-00

By:   
Ian Olsen

Title: President & CEO

Address: 23172 Plaza Pointe Drive, Suite 285  
Laguna Hills, CA 92653

L:\DOCS\DNW\DNW-2302.DOC: clk  
070700